

WHA3000PN

Hot air station 110 V
Product no.: WHA3000PN




Benefits

- > Hot Air Station With Internal Pump
- > Suitable for repairs of fine-pitch components with a large no. of leads
- > The hot air pencil has vacuum pickup for easy component removal
- > The vacuum pickup feature is activated automatically during the process
- > Temperature and air flow are controlled independently
- > Controlled output maintains set temp regardless of air flow setting


For this purpose, we recommend:



Solder fume extractors



Soldering irons



Cleaning



Pre-heating plates



Technical Data

Dimensions L x W x H (mm)	240 x 270 x 170 mm (9,44 x 10,63 x 6,69 inch)
Dimensions L x W x H (inches)	---
Weight (approx.) in kg	---
Voltage	120 V
Power	600 W
Channels	---
Temperature range (depends on tool) °C	50 - 550
Temperature range (depends on tool) °F	122 - 1022
Temperature accuracy °C	± 30 °C (± 54 °F)
Temperature accuracy °F	---
Temperature stability °C	---
Temperature stability °F	---
Equipotential bonding socket	---
Display	---
Air consumption l/min	5 - 50 l / min
Operating pressure in bar/psi	---
Capacity l/min	---
Vacuum	-0,6 bar

Owning the bench



PROFESSIONAL



FILTRATION



EREM



XCELITE